



Main

Range of product	XW
Device short name	XW4548-120/240-60
Product or component type	Hybrid inverter / charger
Network number of phases	Single phase
Type of signal	True sine wave
Continuous power	4500 W - 120 V AC (tolerance: +/- 3 %) 4500 W - 240 V AC (tolerance: +/- 3 %)

Complementary

Feature available	40 A for phase to phase (L-L), duration : 20 s 75 A for phase to neutral (L-N), duration : 20 s
Network frequency	60 Hz +/- 0.1 Hz (output)
Cos phi	0.98
Harmonic distortion	< 5 %
Input voltage	240 V AC (L-L) - bypass/charge mode 120 V AC (L-N) - bypass/charge mode 50.4 V DC
Input voltage limits	214...260 V +/- 3.0 V AC (L-L) - sell mode 108...130 V +/- 1.5 V AC (L-N) - sell mode 160...270 V AC (L-L) - bypass/charge mode 80...150 V AC (L-N) - bypass/charge mode 44...64 V DC
Input current	96 A DC at rated power
Input frequency	44...70 Hz - bypass/charge mode (allowable) 55...65 Hz - bypass/charge mode (default) 59.4...60.4 Hz +/- 0.05 Hz - sell mode
Charging current	85 A
Efficiency	90.2 % - maximum charge rate 93 % CEC weighted 95 % - low-load
Power consumption in W	< 8 W - search mode
Communication network type	Xanbus
Device mounting	Wall mounted
Provided equipment	Battery temperature sensor included for temperature compensation
Height	580 mm
Width	410 mm
Depth	230 mm
Product weight	53.5 kg

Environment

NEMA degree of protection	NEMA Type 1
Ambient air temperature for operation	-25...70 °C
Standards	UL 1741 CSA C22.2 No 107.1
Product certifications	FCC Class B

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.